

DICENTIS Charger for 5 Batteries

www.boschsecurity.com



BOSCH
Invented for life



- ▶ Simultaneous charging of up to 5 Battery Packs
- ▶ Individual Battery Pack charging capacity indicators
- ▶ Recharges from empty in less than 3 hours
- ▶ Auto-ranging power supply, 100–240 Vac
- ▶ Loop-through mains power supply connectors

This Charger (DCNM-WCH05) can simultaneously charge up to 5 Battery Packs (DCNM-WLIION). The charging status of each Battery Pack is shown on individual charge capacity LED indicators. The Battery Packs can be left in the Charger when fully charged. This has no impact on charging level and life time of the Battery Packs.

The Charger is intended for wall mounting, but is also suitable for tabletop use.

The loop-through mains power supply sockets allows a maximum number of chargers to be connected in series to share from the same mains power supply outlet:

- A maximum of 2 chargers can be connected in series for 100-127 Vac, 50-60 Hertz regions at 10A.
- A maximum of 5 chargers can be connected in series for 220-240 Vac, 50-60 Hertz regions at 10A.

Functions

Controls and Indicators

- Five individual Battery Pack charging capacity LED indicators.
- Mains power supply on/off LED indicator.

Interconnections

- Mains power supply socket.
- Loop-through mains power supply socket.

- Battery pack charging connector.

Certifications and approvals

EU	CE, WEEE
US	UL, FCC
CA	CSA, ICES-003
KR	KC
AU/NZ	RCM
JP	PSE
CN	China RoHS
SA	SASO

Parts included

Quantity	Components
1	DCNM-WCH05 Charger for 5 Battery Packs
1	US power cord
1	Eu power cord

Technical specifications

Electrical

Supply Voltage	100-240 Vac +/- 10 % 50/60 Hz
Maximum power consumption	300 W

Mechanical

Dimensions (H x W x D)	340 x 195 x 82 mm (13.4 x 7.6 x 3.2 in)
Weight (without batteries)	1.8 kg (3.97 lb)
Color	Traffic black (RAL 9017)

Environmental

Operating temperature	5 °C to +45 °C (41 °F to +113 °F)
Storage temperature	-20 °C to +70 °C (-4 °F to +158 °F)
Relative humidity	< 95 %, > 5 %

Ordering information

DICENTIS Charger for 5 Batteries

Charger for charging up to 5 Battery Packs (DCNM-WLIION). Color traffic black: RAL 9017.

Order number **DCNM-WCH05**

DICENTIS Charger for 5 Batteries (JP)

Charger (Japanese version) for charging up to 5 Battery Packs (DCNM-WLIION). Color traffic black: RAL 9017.

Order number **DCNM-WCH05-JP**

Accessories

DICENTIS Battery Pack

Battery Pack for Wireless Device (DCNM-WD and DCNM-WDE), lithium-ion, 7.5 Vdc, 12800 mAh, color: Charcoal.

Order number **DCNM-WLIION**

Represented by:

Americas:

Bosch Security Systems, Inc.
12000 Portland Avenue South
Burnsville MN 55337, USA
Phone: +1-800-392-3497
Fax: +1-800-955-6831
audiosupport@us.bosch.com
www.boschsecurity.com

Europe, Middle East, Africa:

Bosch Security Systems B.V.
P.O. Box 80002
5617 BA Eindhoven, The Netherlands
Phone: + 31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2808
Fax: +65 6571 2699
apr.securitysystems@bosch.com
www.boschsecurity.asia

China:

Bosch (Shanghai) Security Systems Ltd.
201 Building, No. 333 Fuquan Road
North IBP
Changning District, Shanghai
200335 China
Phone +86 21 22181111
Fax: +86 21 22182398
www.boschsecurity.com.cn

America Latina:

Robert Bosch Ltda Security Systems Division
Via Anhanguera, Km 98
CEP 13065-900
Campinas, Sao Paulo, Brazil
Phone: +55 19 2103 2860
Fax: +55 19 2103 2862
latam.boschsecurity@bosch.com
www.boschsecurity.com