

# CHM99

HANGING CARDIOD CONDENSER MICROPHONE

[Features](#) [Specs](#) [Downloads](#)

## AN EASY JOB

*for use in houses of worship, conference rooms and theaters*

The CHM99, part of the 99ers Series, is a hanging microphone module with cardioid polar pattern, used to record music or speech in houses of worship, conference rooms or on theater stages. The CHM99 is available in black or white.

A 10m (33ft) special cable that is treated specially to reduce twisting to a minimum and a spring steel hanging clamp for precise microphone alignment keeps the microphone securely in its position. The attached phantom power adapter connects to any standard mixer input with 9V to 52V power supply.

### Compact solution

for plug and play

### Wide pickup angle

for unobtrusive pickup in difficult places

### Twist-free cable

to fix and secure the designated mic position

### Spring steel hanging clamp included

for quick and hassle-free installation

### Available in black and white


blends perfectly into its environment



## TECHNICAL SPECIFICATION

<b>General</b>	Audio frequency bandwidth	70 to 18000 Hz
	Equivalent Noise Level	21 dB-A
	Sensitivity	18 mV/Pa
	Signal to Noise	73 dB-A
	Electrical Impedance	600 Ohms
	Recommended Load Impedance	2000 Ohms

**Polar Patterns**      Cardioid



<b>Powering Interface</b>	Voltage	9 to 52 V
	Current	3 mA

<b>Audio Output</b>	Type	Balanced XLR
	Gender	Male
	Contacts	3-pin

<b>Design</b>	Finish	matte black or white
---------------	--------	----------------------

<b>Dimensions / Weight</b>	Height	55 mm
	Diameter	13.5 - 13.5 mm
	Net Weight	20 g